



HPRi Series 3 Phase 50 Hz 15 to 45 kVA 220/380 Vac Output 120 VDC Modular Inverter System

The Philtek HPRi 3 Phase Modular Inverter System features *expansion* and *redundancy* capabilities.



Inverter System as shown above:
30 kVA 3 Phase Dual Redundant Output



The System is comprised of:

Inverter Modules “Plug and Play”

- 5 or 10 KVA output each, one for each Phase
- Modules are the same as used in the single phase inverter system
- High frequency PWM technology, quiet operation
- “Hot Pluggable”, allows installation or removal of modules without de-energizing the system
- Output compatible with Active Power Factor Corrected AC Loads

Static Bypass Switch and Controller

- Output power rating self configured, 2.5 mSec transfer time
- Microprocessor Controlled with LCD display and Industrial style LED Mimic Diagram
- User configured to operate in the On-line (Inverter preferred) or the Off-line (AC line preferred) mode
- Provides an additional level of redundancy when operated in the On-line Mode
- Plug in modular construction, can be removed or installed with no output interruption during Maintenance Bypass
- Optional RS-232 Communication Port available

AC Power Plant

- Constructed of heavy duty 23” racks
- Make Before Break Maintenance Bypass Switch provides uninterrupted output during bypass
- AC line Circuit Breaker for overload protection during Static Bypass
- Fully enclosed AC and DC power bus bars, pre-wired to terminal blocks for external connections
- Docking caddies provide easy plug in and removal of Inverter Modules
- Compact design, 30 KVA system is only 24.5” x 29” in foot print and 84” in height
- **CSA Certified**

System Specifications *(Subject to change without notice)*

DC Input

Nominal	120 V
Range	105 to 145 V
Current	See Table

AC Output

Power	See Table
Connection	4 wires (Y) + Gnd
Voltage	220/380V 3 Phase 50 Hz
Regulation	± 1%
Dynamic Regulation:	
100 % step load	± 4%
Recovery	< 8 mSec
Efficiency	89 %
Distortion (linear load)	< 1.0 % THD
Non Linear Load Capability	Up to 100 %
Active P.F. Corrected Loads	Compatible
Load Power Factor (PF)	0.8
Frequency Tolerance	± 0.1 % free running
Overload	120 % for 10 minutes
Synchronization:	
Range	± 1.5 Hz
Rate	1 Hz per Sec

Bypass AC

Connection	4 wires (Y) + Gnd
Voltage	220/380V 3Phase 50 Hz
Current	Same as output current see Table

Static Bypass Switch

Transfer Time	2.5 mSec typical 5 mSec maximum
Voltage Tolerance	± 10 %
Frequency Tolerance	± 1.5 Hz
Overload:	120 % for 10 Minutes 1000 % for 8 ms

Environmental

Temperature	0° C to 40° C
Humidity	95 % RH
Cooling	Forced Air with temperature Controlled Fans

Inverter Modules

<i>Output</i>	<i>Model #</i>
5 kVA	HPri-INV-5K-120-A
10 kVA	HPri-INV-10K-120-A

Inverter System 120 VDC input 220/380 VAC 50 Hz 3 Phase Output

Output VA @ 1.0 PF	15,000 VA	30,000 VA	45,000 VA
AC Power Plant + Controller Model #	HPri 45K-120-3A	HPri 45K-120-3A	HPri 45K-120-3A+R3A
Inverter Modules Required	3 x 5 kVA	3 x 10 kVA	3 x 5 KVA + 3 x 10 kVA
AC Output Current per Phase	23 Amp AC	45 Amp AC	91 Amp AC
DC Input Current @ 105 V	161 Amp DC	322 Amp DC	161 + 322 Amp DC
AC Power Plant Racks	1	1	3 *
Overall Dim. W"xD"xH"	24.5 x 29 x 84	24.5 x 29 x 84	49 x 29 x 84
Total Weight (Net)	990 Lbs.	1,350 Lbs.	2,150 Lbs.

N+1 Redundant System 120 VDC input 220/380 VAC 50 Hz 3 Phase Output

Output VA @ 1.0 PF	15,000 VA N+1	30,000 VA N+1
AC Power Plant + Controller Model #	HPri 45K-120-3A+R3A	HPri 45K-120-3A+R3A
Inverter Modules Required	6 x 5 kVA	6 x 10 kVA
AC Output Current per Phase	23 Amp AC	45 Amp AC
DC Input Current @ 105 V	161 Amp DC	322 Amp DC
AC Power Plant Racks	2 *	2 *
Overall Dim. W"xD"xH"	49 x 29 x 84	49 x 29 x 84
Total Weight (Net)	1,930 Lbs.	2,570 Lbs.

* AC Power Plant shipped disassembled

Ordering Information:

First determine your power requirement, then select the appropriate **AC Power Plant + Controller** and quantity of **Inverter Modules** from the above tables

For example:

30,000VA output with N+1 redundancy requires

Qty 1	HPri 45K-120-3A+R3A
Qty 6	HPri-INV-10K-120-A

For More Information please Contact:

In Canada

In USA

Philtek Electronics Ltd.

Philtek Power Corp.

Tel: (604) 270-4642

Tel: (360) 332-7252

Fax: (604) 270-8343

Fax: (360) 332-7253

www.philtek.com

(Printed in Canada 1298)